

PROTECH™

51-23017-32 THREE SPEED DOUBLE SHAFT MOTOR CAN BE USED TO REPLACE MOST 115 VOLT BLOWER MOTORS FROM 1/3 TO 3/4HP BY CHANGING CAPACITORS AND SPEEDS.

CAPACITOR AND MOTORS SPEED SELECTION CHART FOR VARIOUS HP APPLICATIONS.

Motor	Speed to use	Capacitor *	FLA
3/4 HP	High	10/370	13.3
		12 1/2/370	12.8
		15/370 •	12.4
1/2 HP	Medium	10/370	10.1
		12 1/2/370	9.6
		15/370	9.2
1/3 HP	Low	10/370	6.9
		12 1/2/370	6.2
		15/370	5.8

• Design Capacitor

* MOTOR CAN BE RUN WITH 10, 12 1/2 AND 15/370 CAPACITORS FOR ALL RATINGS; HOWEVER, MOTOR IS APPROXIMATELY 10% STRONGER WITH THE 12 1/2 AND 15 MFD CAPACITORS AND HAS HIGHER STARTING AND RUNNING TORQUE. RECOMMENDED 12 1/2 OR 15 MFD FOR 3/4 HP RATING.

