

One-On-One™ Direct Replacement Motors



	MARS NO.	MFG. NO	HP	VOLTS	RPM/SPEEDS	ROT	AMPS	DIMENSIONS		
								A	B	C
Kramer/Trenton (con't)										
	09932	253-1194	1/20	115	1550/1	CCW OSE	1.9	2.25	2.75	-
	3.3 inch diam., open, 5/16 inch shaft, shaded pole with Lyall plug									
	Replaces: A.O Smith 1101; Fasco D1101; Larkin 253-1194; Magnetek 574									
										
	09933	253-1195	1/20	208-230	1550/1	CCW OSE	1.3	2.25	5.0	-
	3.3 inch diam., open, 5/16 inch shaft, shaded pole with Lyall plug									
	Replaces: A.O. Smith 1103; Fasco D1103; Larkin 253-1195; Magnetek 575									
										
Larkin Coil										
	D1101	-	1/20	115	1500/1	CCW SE	1.9	2.25	2.75	-
	Shaded pole, sleeve bearing, 5/16 inch dia. shaft, special low temp oil (-40°F)									
	Replaces: Larkin No. 253-1194, Fasco No. 7163-2113									
										
	D1103	-	1/20	208 - 230	1500/1	CCW SE	1.15	2.25	3.00	-
	Shaded pole, sleeve bearing, 5/16 inch dia. shaft, special low temp oil (-40°F), not a direct replacement for 253-1194, but is an acceptable substitute									
	Replaces: Fasco No. 7163-3371, 252-1195									
										
	D863	-	1/2	208 - 230	1075/1	REV	4.0	3.00	6.75	-
	PSC, ball bearing, 7.5@370V capacitor required (MARS No. 12007)									
	Replaces: SCS0500HI-CPM120-3, 5KCP39PGH728T									
										
Lear Siegler										
	D1046	-	1/8	115	1050/1	CW SE	5.1	2.25	3.00	-
	Shaded pole, sleeve bearing									
	Replaces: 305313-000-165, 7151-0073, 7151-2826									
										